

DTV4X8

MULTI-SATELLITE

4 in 8 OUT MULTI-SWITCH

4 in 8 out with F-connection power supply. For use with DIRECTV Multi-Sat installs or single-sat installs requiring more than 4 receivers.



Model Number	DTV4X8
Frequency Range	
Satellite	950 – 1450 MHz
Off-air	None
Satellite	
Insertion Loss / Gain	0 to +5 dB
Same Sat. Cross-Pol. Isolation	30 dB
Diff. Sat. Cross-Pol Isolation	35 dB
Selection Control Voltage	
18V (101 LHCP)	17.9 – 18.9VDC
13V (101 RHCP)	12.8 – 13.5VDC
18V 22kHz (119 LHCP + 110	17.9 – 18.9VDC, w
13V 22kHz (119 RHCP)	12.8 – 13.5VDC, w
Off-air	
Insertion Loss	N/A
Others	
Output Ports	8
Indoor or Outdoor	Outdoor/Indoor
22kHz Tone Output at 18V22kHz and 13V22kHz	Yes
DC Adapter Requirement	Required
Dimensions	8.3"x2.3"x1.4"
DC Adapter	
AC Input	115 VAC
DC Output Voltage	24 VDC
Max DC Current	1000 mA